

## Coil code table

AC						DC		Semi-electric (AC)		Electric (AC/DC)	
50Hz		60Hz		50/60Hz		-		50/60Hz		-	
Coil voltage(V)	code	Coil voltage(V)	code	Coil voltage(V)	code	Coil voltage(V)	code	Coil voltage(V)	code	Coil voltage(V)	code
24	B5	24	B6	24	B7	12	JD	100-120	HF	24 (AC24-25 50/60Hz, DC24)	AV
32	C5	32	-	32	-	20	AD	220-240	MU	48 (AC48-50 50/60Hz, DC24)	BV
36	CB5	36	-	36	CB7	24	BD	300 (265-247)	OQ	24/48 (AC24-50 50/60Hz, DC24-48)	CV
42	D5	42	-	42	D7	30	PD	380-440	OV	100/100 (AC100-127 50/60Hz, DC100-110)	DV
48	E5	48	E6	48	E7	36	CD	500 (440-575)	S7	100/200 (AC100-240 50/60Hz, DC100-220)	FV
65	GE5	65	GE6	65	GE7	42	ID	100-120 (LED)	HFL	200/200 (AC200-240 50/60Hz, DC200-220)	EV
80	G5	80	-	80	-	48	ED	220-240 (LED)	MUL	300/400 (AC265-450 50/60Hz)	GV
100	H5	100	-	100	H7	60	ND	380-440 (LED)	QVL	AC 300 (AC265-347 50/60Hz)	HV
110	F5	110	F6	110	F7	72	SD			AC 400 (AC380-450 50/60Hz)	IV
100/110	-	100/110	-	100/110	HF7	80	KS			AC 500 (AC440-575 50/60Hz)	JV
115	FE5	115	FE6	115	FE7	100	HD				
110/120	-	110/120	-	110/120	HK7	110	FD				
120	K5	120	K6	120	K7	120	KD				
127	KB5	127	KB6	127	KB7	125	GD				
175	LC5	175	LC6	175	LC7	200	LD				
200	L5	200	L6	200	L7	220	MD				
200/208	-	200/208	-	200/208	LJ7	240	OD				
208	LB5	208	LB6	208	LB7	250	UD				
220	M5	220	M6	220	M7						
200/220	-	200/220	-	200/220	LM7						
220/230	-	220/230	-	220/230	MP7						
220/240	-	220/240	-	220/240	MU7						
220L	M5L	220L	M6L	220L	M7L						
230	P5	230	-	230	P7						
240	U5	240	U6	240	U7						
240W	U5W	240W	-	240W	-						
230/240	PU5	230/240	PU6	230/240	PU7						
240/277	-	240/277	-	240/277	UO7						
256	A5	256	A6	256	A7						
277	O5	277	O6	277	O7						
380	Q5	380	Q6	380	Q7						
400	V5	400	-	400	V7						
380/400	-	380/400	-	380/400	QV7						
415	N5	415	N6	415	N7						
440	R5	440	R6	440	R7						
400/440	-	400/440	-	400/440	VR7						
460	-	460	-	460	RW7						
480	W5	480	W6	480	-						
500	S5	500	-	500	S7						
550	X5	550	-	550	X7						
600	T5	600	T6	600	-						